

Funktionsbeschreibung

Der SPATZ HDMI-4i 1.3 schaltet alle HDMI und DVI Signale inklusive der neuen höheren Bandbreiten, wie Sie mit HDMI 1.3 vorgestellt wurden

Das Gerät unterstützt bis zu 2,25 Gbps Bandbreite und alle Audioformate inklusive DOLBY DIGITAL TRUEHD und DTS-HD.

Selbstverständlich ist der Umschalter mit allen anderen Signalarten abwärtskompatibel.

Die Eingänge können zyklisch mit dem Fronttaster angewählt werden, oder direkt mit der Infrarotfernbedienung umgeschaltet werden.

Technische Daten

Versorgung	DC 5V
Videoeingang	4 x DVI oder HDMI (HDCP)
Videoausgang	1 x DVI oder HDMI (HDCP)
Unterstützte Auflösungen	480i –1080p
unterstützte Frameraten	24-120 Hz
Grösse	200 x 104 x 25 mm

Functional description

The SPATZ HDMI-4i 1.3 switches up to 4 HDMI or DVI sources to a single HDMI output.

The unit is fully compatible with the new HDMI 1.3 Standard capable of passing the new higher bandwidth signals. of up to 2,25 Gbps

The switcher supports 30/36/48 Bit color depth and DOLBY DIGITAL TRUEHD und DTS-HD audio.

It is fully downward compatible to older HDMI and DVI standards

Inputs maybe switched with the front button or direct acces via IR remote.

Technical Data

Power supply voltage	DC 5V
Video input	DVI or HDMI (HDCP)
Video output	DVI or HDMI (HDCP)
supported resolutions	480i –1080p
supported framerates	24-120 Hz
Dimension	200 x 104 x 25 mm